



D-304286



Visonic

SD-304C PG2

PowerG, Wireless Shock and Contact detector with Wired Input

Installation Instructions

English

1. INTRODUCTION


The SD- 304C PG2 is a wireless PowerG innovative shock detector with optional magnetic contact and auxiliary input interfacing with all PowerMaster control panels, version 16 or higher. The SD-304C PG2 fits windows, doors, walls or roofs and is ideal for residential or commercial installations. It detects and analyzes gross attacks or a series of low level shocks (up to 10 low level shocks within 30 seconds) and provides early warning of any attempt of intrusion before a burglar actually breaks-in.

The detector incorporates:

- A shock / vibration piezoelectric sensor.
- Optional reed switch.
- Optional auxiliary input to use with installer supplied contacts or other wired devices.

Installer added-value features:

- Digital display enables fast and easy shock level adjustment
- Full remote configuration from PowerMaster control panel or Monitoring Station saves the need to physically access the shock detector for configuration
- Remote view of: Low Battery, front and back Tamper, Supervision
- An LED lights whenever alarm or tamper events are reported (the LED does not light while a supervision message is being transmitted).



A. Transmission LED
B. Magnet

Figure 1: External View

2. INSTALLATION

2.1 Mounting




Figure 2. Base with P.C. Board Removed

Refer to the Shock Detection Radius, in the Specifications section, according to the surface material used. Install the device in a location where a strong shock impact is expected. The unit should be mounted on a flat surface and firmly fixed using both mounting screws.

For magnetic contact detection, it is highly recommended to attach the detector to the door or window on the fixed frame and the magnet to the movable part (door or window). For optimal magnetic sensor activity and better security it is recommended to apply the magnet as close as possible to the detector's marked side.

Note: Once the cover is removed, a tamper message is transmitted to the control panel. Subsequent removal of the battery prevents transmission of "TAMPER RESTORE", leaving the detector in permanent alert. To avoid this, press the tamper switch while you remove the battery.

Caution!

Risk of explosion if battery is replaced by an incorrect type. Dispose of used battery according to manufacturer's instructions.

Attention! The unit has a back tamper switch (optional) under the PCB. As long as the PCB is seated firmly within the base, the switch lever will be pressed against a special break-away base segment that is loosely connected to the base (Figure 2). **Be sure to fasten the break-away segment to the wall.** If the detector unit is forcibly removed from the wall, this segment will break away from the base, causing the tamper switch to open.




Figure 3. Mounting

Note: Use a manual or electronic screwdriver. Do not use a drill as a screwdriver.

1. Insert a flat-edged screwdriver into the slot and push upward to remove cover.
2. Remove screw.
3. Separate base from cover.
4. Secure the base to the mounting surface using only the screws supplied in the package.
CAUTION! Do not remove the PCB to mark holes. Use one of the following: a slim pencil, nails or the attached paper model.
CAUTION! Do not use double-sided tape, as this will tend to insulate the detector from vibrations.
5. Insert the battery while observing polarity.
6. Mount the magnet near its location mark with 2 screws.

- A. Fixed frame
- B. Moving part

Note: 868 MHz device is illustrated in the example. The same mounting procedure should be performed for 433 MHz and 915 MHz devices.

* This additional screw is used for back tamper only.

2.2 Auxiliary Input Wiring (Fig. 4)

The wired input is not covered by INCERT.

- A. Connect the auxiliary sensor contacts across the SD-304C PG2 auxiliary input terminals.

Note: Maximal guaranteed cable length is 10m.

- B. If the auxiliary input of the SD-304C PG2 is defined as a Normally Closed (N.C.) type, series connected N.C. sensor contacts must be used exclusively. An alarm message is transmitted once the loop is opened.
- C. If the auxiliary input of the SD-304C PG2 is defined as a Normally Open (N.O.) type, parallel connected N.O. sensor contacts must be used exclusively. An alarm message is transmitted once the loop is closed.
- D. For End of Line (EOL) supervision:
Normally Closed (N.C.) or Normally Open (N.O.) sensor contacts can be used, as shown in Figure 4. A 2.2kΩ E.O.L. resistor must be wired at the far end of the zone loop. An alarm message is transmitted once the loop is opened or short circuited.
- E. For Double End of Line (DEOL) supervision:
Two Normally Closed (N.C.) sensor contacts can be used, as shown in Figure 4. Two 2.2kΩ E.O.L. resistors must be wired at the far end of the zone loop which is opened or short circuited. Events messages are transmitted according to connected inputs, for example, Alarm or Tamper contacts.




Figure 4. AUX Input Wiring Examples

2.3 Enrollment

Refer to the PowerMaster panel's Installer Guide and follow the procedure under the "02:ZONES/DEVICES" option of the Installer Menu. A general description of the procedure is provided in the following flow chart.

Step 1	Step 2	Step 3	Step 4
Enter the Installer menu and select "02:ZONES/DEVICES"	Select "ADD NEW DEVICE" See Note 1	Enroll the detector: press the enroll button and then release it as soon as the yellow LED lights, or, enter the device ID (on the back of device)	Select the desired Detector Number for the new device
02.ZONES/DEVICES	ADD NEW DEVICES	ENROLL NOW or ENTR ID:XXX-XXXX	Z02:Shk+AX+CntG3 ID No. 170-XXXX
MODIFY DEVICES			
Step 5	Step 6	Step 7	Step 8
Configure Location and Zone Type Parameters	Enter PARTITIONS. See Note 2	Assign partitions by pressing the 1, 2 and 3 buttons	Select "Device Settings" and see below to configure the (AUX) button.
Z02.LOCATION Z02.ZONE TYPE	Z02:PARTITIONS	Z02:P1 P2 P3	Z02:DEV SETTINGS

Notes:

1. If the shock detector is already enrolled, you can configure the device parameters and assign partitions via the “**Modify Devices**” option – see Step 2.
2. PARTITIONS will appear only if PARTITIONING was previously enabled in the panel.

2.4 Configuring the Device Parameters

Enter the **Device Settings** menu and follow the configuration instructions for the SD-304C PG2 shock detector as described in the following table.

Option	Configuration Instructions
Alarm LED	Determine whether or not the alarm LED indication will be activated. Optional settings: ON (default) or OFF .
Reed Switch	Determine whether to enable or disable the internal reed switch. Optional settings: Enabled or Disabled (default).
AUX input	Define the external input according to the installer's requirements. Optional settings: Disabled (default), End of Line , Normally open , Normally close or Double EOL .
Sens. Threshold	Define the sensitivity threshold of the shock detector when configuring from the panel. Optional settings: Sens. Thresh. 1 to Sens. Thresh. 19 (default setting is Sens. Thresh. 8). <i>Note: Configuration of this feature can be performed either from the panel or from the device on condition that the device was already enrolled and there is synchronization between the panel and device. If an “E” appears on the device’s digital display, this indicates no synchronization.</i>
Accumulated	Define whether Accumulation mode, when configuring from the panel, is Enabled or Disabled. Optional settings: Enabled or Disabled (default).

2.5 Local Operating and Calibrating of the Shock Detector

The SD-304C PG2 can be calibrated locally only when the device is in Local Diagnostics mode (first 15 minutes after opening the cover). When the device is not in this mode, but further calibration is required, the installer should reset the device by closing the tamper switch.

1. Press on the "Up" or "Down" button to turn on the digital display. The letter 'G' appears on the display for 3 seconds to indicate Gross Attack levels (thresholds). Then, the menu appears on the display to enable you to select a number in the range of 1-19. If, instead of a number the letter "E" appears on the display, this indicates that there is no communication link between the unit and control panel and, therefore, local adjustment is not allowed.
Note: If no buttons are pressed within 20 seconds, the digital display turns off.
2. Change the threshold by pressing the "Up" or "Down" button.
Note: The lower the threshold, the higher the sensitivity, therefore, the lowest thresholds are more suitable for harder materials, such as concrete.
3. While the SD-304C PG2 threshold menu is active, knock on the surface with the required force for the detector to set the required threshold. The power of the detected knock will be presented on the display of the SD-304C PG2 as a blinking number for 3 seconds. The displayed number will be in the range of 1 to 19, where 1 is very weak and 19 is very strong.
Note: If the installer knocks on the surface but nothing appears on the display, this indicates that no shock is detected. If a hyphen blinks, this indicates that the knock is above the highest threshold of the detector.
4. Repeat the same test several times.
5. Press the "Up" or "Down" button to navigate to the threshold number to be set and then press the "Up" and "Down" buttons simultaneously to set the threshold.
6. The detector now moves to the next menu, the Accumulated menu (shown as "A" on the display). Press the "Up" or "Down" buttons to Enable ("1" on the display) or Disable ("0" on the display) the Accumulation mode. Press the "Up" or "Down" buttons simultaneously to set the selected option.
Note: When Accumulation is enabled, the power of impact will still indicate the strength of a single knock, therefore, it is recommended to disable this parameter while the Threshold is tested and to enable the Accumulation mode only after setting the Threshold.
7. If after the "Up" and "Down" buttons are simultaneously pressed the letter "E" appears, this likely indicates that there is no communication link between the unit and control panel. Check if the panel is properly powered.

3. LOCAL DIAGNOSTICS TEST

Before testing, separate the base from the cover (see Figure 3).

- A. Press the tamper switch once and release it.
- B. Put back the cover to return the tamper switch to its normal (undisturbed) position, and then secure the front cover to the base with the case closure screw.
- C. Use a hammer to apply shock in close proximity to the detector and verify the red LED blinks, indicating detection.
- D. After 2 seconds the LED blinks 3 times.

The following table indicates received signal strength indication.

LED response	Reception
Green LED blinks	Strong
Orange LED blinks	Good
Red LED blinks	Poor
No blinks	No communication

IMPORTANT! Reliable reception must be assured. Therefore, "poor" signal strength is not acceptable. If you receive a "poor" signal from the device, re-locate it and re-test until a "good" or "strong" signal strength is received.

Note: For detailed Diagnostics Test instructions, refer to the control panel Installer Guide.

4. EVENT INDICATIONS

LED Indications	Event
Red LED ON 0.2 sec.	Tamper open / close
Red on 2 sec.	Shock
Red on 2 sec.	Open close door
Red on 2 sec.	Open close Aux input

5. MISCELLANEOUS COMMENTS

Visonic Ltd. wireless systems are very reliable and are tested to high standards. However, due to low transmitting power and limited range (required by FCC and other regulatory authorities), there are some limitations to be considered:

- A. Receivers may be blocked by radio signals occurring on or near their operating frequencies, regardless of the digital code used.
- B. A receiver responds only to one transmitted signal at a time.
- C. Wireless devices should be tested regularly to determine whether there are sources of interference and to protect against faults.

6. COMPLIANCE WITH STANDARDS

Compliance with Standards



The SD-304C PG2 complies with the following standards:

Europe: EN 301 489-3, EN 50130-4, EN 300 220-2, EN 62368-1, EN 50131-5-3, EN 50130-5, EN 50131-1, EN 50131-6 Type C, EN 50131-2-8, EN 50131-2-6, Grade 2, Class II.

Certified by Applica Test & Certification AS in accordance with EN 50131-2-6 EN 50131-2-8, EN 50131-5-3, EN 50131-6, EN 50130-4, EN 50130-5.

UK: This product is suitable for use in systems installed to conform to PD6662

USA: CFR 47 part 15 (FCC)

Canada: RSS-247, RSS-102

Hereby, Visonic Ltd. declares that the radio equipment type SD-304C PG2 is in compliance with Directive 2014/53/EU. The full text of the EU declaration of conformity is available at the following internet address:

<http://www.visonic.com/download-center>.

This device complies with Part 15 of the FCC Rules and with ISSED license-exempt RSS standard(s). Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Le présent appareil est conforme aux CNR d'ISED applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes : (1) l'appareil ne doit pas produire de brouillage, et (2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

To comply with FCC and IC RF exposure compliance requirements, the device should be located at a distance of at least 20 cm from all persons during normal operation. The antennas used for this product must not be co-located or operated in conjunction with any other antenna or transmitter.

Le dispositif doit être placé à une distance d'au moins 20 cm à partir de toutes les personnes au cours de son fonctionnement normal. Les antennes utilisées pour ce produit ne doivent pas être situées ou exploitées conjointement avec une autre antenne ou transmetteur.

The digital circuitry of this device has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in residential installations. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio and television reception. However, there is no guarantee that interference will not occur in a particular installation. If this device does cause such interference, which can be verified by turning the device off and on, the user is encouraged to eliminate the interference by one or more of the following

measures:

- Re-orient or re-locate the receiving antenna.
- Increase the distance between the device and the receiver.
- Connect the device to an outlet on a circuit different from the one which supplies power to the receiver.
- Consult the dealer or an experienced radio/TV technician

This Class B digital apparatus complies with Canadian ICES-003.

Cet appareil numérique de la classe B est conforme a la norme NMB-003 du Canada.

WARNING!

To comply with FCC and IC RF exposure compliance requirements, the device should be located at a distance of at least 20 cm from all persons during normal operation. The antennas used for this product must not be co-located or operated in conjunction with any other antenna or transmitter.

WARNING!

The user is cautioned that changes or modifications to the unit, not expressly approved by Visonic Ltd., could void the user's FCC or other authority to operate the equipment.

Wood		Supports	Soft Iron	
Opening	Closing	Direction	Opening	Closing
20mm+/-5mm	15mm+/-5mm	X	13mm+/-5mm	11mm+/-5mm
15mm+/-5mm	13mm+/-5mm	Y	14mm+/-5mm	12mm+/-5mm
26mm+/-5mm	24mm+/-5mm	Z	26mm+/-5mm	24mm+/-5mm





Figure 5: Axis Definitions



W.E.E. Product Recycling Declaration

For information regarding the recycling of this product you must contact the company from which you originally purchased it. If you are discarding this product and not returning it for repair then you must ensure that it is returned as identified by your supplier. This product is not to be thrown away with everyday waste.
 Directive 2012/19/EU Waste Electrical and Electronic Equipment.

APPENDIX: SPECIFICATIONS

- Frequency Band (MHz)
- Maximum Tx power
- Communication Protocol
- Alarm Input
- Tamper
- Supervision
- Tamper Alert
- Power Supply
- Battery type
- Battery Life Expectancy
- Low Battery Threshold
- Current Consumption
- Shock Detection Radius and Sensitivity Level

Europe and rest of world: 433-434, 868-869 USA: 912-919

10 dBm @ 433 MHz, 14 dBm @ 868 MHz

PowerG

One auxiliary

Front and back

Signaling at 4-min. intervals

Reported when a tamper event occurs

Type C

3 V Lithium CR-123A type battery, Panasonic, Sanyo or GP only.

5 years (for typical use) with all sensors enabled

2.6 V

20 – 30 µA approx. (150 mA during transmission)

Not EN Tested		EN Certified		
Plate material	Shock detection radius	Plate material	Shock detection radius	Sensitivity level
Window	4M	Framed glass window (standard test material A1)	1M	15
Wood	3.5M	Wooden plate (Standard test material A2)	1M	12
Brick/concrete walls	2.5M	Concrete plate (Standard test material A3)	0.5M	4

Operating Temperature

-10°C to 55°C (14°F to 131°F)

Storage Temperature

-20°C to 60°C (-4°F to 140°F)

Humidity

Average relative humidity of approximate 75% non-condensing. For 30 days per year relative humidity may vary between 85 % and 95 % non-condensing

Auxiliary Input Cable Length

10m max.

Auxiliary Input EOL Resistor

2.2 KΩ

Dimensions (LxWxD)

118 x 27 x 30 mm (4-5/8 x 1-1/8 x 1-3/16 in.)

Weight (including battery)

130g (4.6 oz)

WARRANTY

Visonic Limited (the "Manufacturer") warrants this product only (the "Product") to the original purchaser only (the "Purchaser") against defective workmanship and materials under normal use of the Product for a period of twelve (12) months from the date of shipment by the Manufacturer.

This Warranty is absolutely conditional upon the Product having been properly installed, maintained and operated under conditions of normal use in accordance with the Manufacturers recommended installation and operation instructions. Products which have become defective for any other reason, according to the Manufacturers discretion, such as improper installation, failure to follow recommended installation and operational instructions, neglect, willful damage, misuse or vandalism, accidental damage, alteration or tampering, or repair by anyone other than the manufacturer, are not covered by this Warranty.

The Manufacturer does not represent that this Product may not be compromised and/or circumvented or that the Product will prevent any death and/or personal injury and/or damage to property resulting from burglary, robbery, fire or otherwise, or that the Product will in all cases provide adequate warning or protection. The Product, properly installed and maintained, only reduces the risk of such events without warning and it is not a guarantee or insurance that such events will not occur.

THIS WARRANTY IS EXCLUSIVE AND EXPRESSLY IN LIEU OF ALL OTHER WARRANTIES, OBLIGATIONS OR LIABILITIES, WHETHER WRITTEN, ORAL, EXPRESS OR IMPLIED, INCLUDING ANY WARRANTY OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE, OR OTHERWISE. IN NO CASE SHALL THE MANUFACTURER BE LIABLE TO ANYONE FOR ANY CONSEQUENTIAL OR INCIDENTAL DAMAGES FOR BREACH OF THIS WARRANTY OR ANY OTHER WARRANTIES WHATSOEVER, AS AFORESAID.

THE MANUFACTURER SHALL IN NO EVENT BE LIABLE FOR ANY SPECIAL, INDIRECT, INCIDENTAL, CONSEQUENTIAL OR PUNITIVE DAMAGES OR FOR LOSS, DAMAGE, OR EXPENSE, INCLUDING LOSS OF USE, PROFITS, REVENUE, OR GOODWILL, DIRECTLY OR INDIRECTLY ARISING FROM PURCHASER'S USE OR INABILITY TO USE THE PRODUCT, OR FOR LOSS OR DESTRUCTION OF OTHER PROPERTY OR FROM ANY OTHER CAUSE, EVEN IF MANUFACTURER HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

THE MANUFACTURER SHALL HAVE NO LIABILITY FOR ANY DEATH, PERSONAL AND/OR BODILY INJURY AND/OR DAMAGE TO PROPERTY OR OTHER LOSS WHETHER DIRECT, INDIRECT, INCIDENTAL, CONSEQUENTIAL OR OTHERWISE, BASED ON A CLAIM THAT THE PRODUCT FAILED TO FUNCTION.

However, if the Manufacturer is held liable, whether directly or indirectly, for any loss or damage arising under this limited warranty, **THE MANUFACTURER'S MAXIMUM LIABILITY (IF ANY) SHALL NOT IN ANY CASE EXCEED THE PURCHASE PRICE OF THE PRODUCT**, which shall be fixed as liquidated damages and not as a penalty, and shall be the complete and exclusive remedy against the Manufacturer.

When accepting the delivery of the Product, the Purchaser agrees to the said conditions of sale and warranty and he recognizes having been informed of.

Some jurisdictions do not allow the exclusion or limitation of incidental or consequential damages, so these limitations may not apply under certain circumstances.

The Manufacturer shall be under no liability whatsoever arising out of the corruption and/or malfunctioning of any telecommunication or electronic equipment or any programs.

The Manufacturers obligations under this Warranty are limited solely to repair and/or replace at the Manufacturer's discretion any Product or part thereof that may prove defective. Any repair and/or replacement shall not extend the original Warranty period. The Manufacturer shall not be responsible for dismantling and/or reinstallation costs. To exercise this Warranty the Product must be returned to the Manufacturer freight pre-paid and insured. All freight and insurance costs are the responsibility of the Purchaser and are not included in this Warranty.

This warranty shall not be modified, varied or extended, and the Manufacturer does not authorize any person to act on its behalf in the modification, variation or extension of this warranty. This warranty shall apply to the Product only. All products, accessories or attachments of others used in conjunction with the Product, including batteries, shall be covered solely by their own warranty, if any. The Manufacturer shall not be liable for any damage or loss whatsoever, whether directly, indirectly, incidentally, consequentially or otherwise, caused by the malfunction of the Product due to products, accessories, or attachments of others, including batteries, used in conjunction with the Products. This Warranty is exclusive to the original Purchaser and is not assignable.

This Warranty is in addition to and does not affect your legal rights. Any provision in this warranty which is contrary to the Law in the state or country where the Product is supplied shall not apply.

Warning: The user must follow the Manufacturer's installation and operational instructions including testing the Product and its whole system at least once a week and to take all necessary precautions for his/her safety and the protection of his/her property.

1/08

EMAIL: info@visonic.com

INTERNET: www.visonic.com

© 2021 Johnson Controls. All rights reserved. JOHNSON CONTROLS, TYCO and VISONIC are trademarks of Johnson Controls.

D-304286 SD-304C PG2 (Rev 13, 02/22)



D-304286

